

# Max Number of Speakers per Amplifier Channel

	KZ1		KZ14		KV25		KV52		KK52		KK102		KP52		KP102		KY102	
<b>OHM</b>	<b>16</b>	<b>16</b>	<b>8</b>	<b>32</b>	<b>16</b>	<b>64</b>	<b>16</b>	<b>64</b>	<b>8</b>	<b>32</b>	<b>8</b>	<b>32</b>	<b>4</b>	<b>16</b>	<b>8</b>	<b>32</b>		
<b>KA02</b>	4	4	2															
<b>KA14</b>	4	4	2		4		4*											
<b>KA24</b>	4	4		8	4		4		2		2		1					
<b>KA84</b>				8		16		16		8		8		4	2			
<b>KMT12</b>				4		8		8		4		4		2	1			
<b>KMT18</b>						8		8		4		4		2	1			
<b>KMT21</b>								16		8		8		4	2			
<b>KMT218</b>								16		8		8		4	2			

	KT2		KT2-HV	KAN200	KAN200+	KAN200+8	KF26		KF210		KF212	KX12
<b>OHM</b>	<b>8</b>	<b>32</b>	<b>70v</b>	<b>64</b>	<b>32</b>	<b>8</b>	<b>8</b>	<b>32</b>	<b>4</b>	<b>16</b>	<b>8</b>	<b>8</b>
<b>KA02</b>	2						2*					
<b>KA14</b>		8				2	2					
<b>KA24</b>		8		16*	8*	2	2		1		2*	
<b>KA84</b>		8	100	16	8			8		4	2	2
<b>KMT12</b>				8	4			4		2	1	1
<b>KMT18</b>				8	4			4		2	1	1
<b>KMT21</b>				16	8			8		4	2	3
<b>KMT218</b>				16	8			8		4	2	3

	KU26		KU44		KU210		KU212		KTR24	KTR25	KTR26	KMT12P	KMT18P	KMT21P	KMT218P
<b>OHM</b>	<b>8</b>	<b>32</b>	<b>8</b>	<b>32</b>	<b>4</b>	<b>16</b>	<b>4</b>	<b>16</b>	<b>4</b>	<b>4</b>	<b>2</b>	<b>8</b>	<b>8</b>	<b>4</b>	<b>4</b>
<b>KA02</b>									2**	2**	1**				
<b>KA14</b>	2		2		1				1	1					
<b>KA24</b>	2		2		1		1		1	1		2	2		
<b>KA84</b>		8		8		4		4				2	2	1	1
<b>KMT12</b>												1	1		
<b>KMT18</b>												1	1		
<b>KMT21</b>														1	1
<b>KMT218</b>														1	1

	KRM33P	KM112P	RAIL
<b>OHM</b>	<b>8</b>	<b>8</b>	<b>48</b>
<b>KA02</b>			12*
<b>KA14</b>	2		12*
<b>KA24</b>	2		12
<b>KA84</b>	2	2	12
<b>KMT12</b>		1	
<b>KMT18</b>		1	
<b>KMT21</b>		2	
<b>KMT218</b>		2	

Notes for data: \* Not full power

\*\* 2 channels PBTL